
MOUNTING KITS FOR PRECISION DIGITAL METERS

PDA6545 2" PIPE MOUNTING KIT




PARTS SUPPLIED:


- 1. One mounting plate
- 2. Two 2" U-bolt kits
- 3. Four ⁵/₁₆" 18 x 1¹/₄" screws
- 4. Four 5/16" 18 hex nuts
- 5. Four 5/16" flat washers
- 6. Four 5/16" lockwashers
- 7. Four #6 32 x ¾" screws
- 8. Four #6 32 hex nuts
- 9. Four #6 32 lockwashers

~ 0		Hardware Usage Table (Refer to Parts Supplied)								
		1	2	3	4	5	6	7	8	9
Meter Type	Holes									
PD655	А	Х	Х					Х	Х	Х
PD656	В	Х	Х	Х	Х	Х	Х			
PD687*	С	Х	Х	Х	Х		Х			
PDA2407, PDA2408	D	Х	Х	Hardware Supplied with Enclosure						
PDA2444-PDA2446	E	Х	Х	Х	Х	Х	Х			
PDA2811-PDA2812	F	Х	Х					Х	Х	Х
*Note: PDA6545 provides four mounting hole for PD687: PDA6845 provides two mounting holes.										

Note: PDA6545 provides four mounting hole for PD687; PDA6845 provides two mounting holes.

PDA6845 2" PIPE MOUNTING KIT





(208 mm)

ORDERING INFORMATION

Model	Description	Mounting Holes	Weight Ib (kg)
PDA6545	2" Pipe Mounting Kit Zinc Plated Steel	4	3.0 (1.4)
PDA6545-SS	2" Pipe Mounting Kit Stainless Steel	4	3.0 (1.4)
PDA6845	2" Pipe Mounting Kit Zinc Plated Steel	2	1.1 (0.5)
PDA6845-SS	2" Pipe Mounting Kit Stainless Steel	2	1.1 (0.5)

PRECISION DIGITAL CORPORATION

HOLES	METER TYPE
1	PD675, PD685, PD686, PD697
2	PD677, PD698
3	PD660
4	PD687*
5	PDA2801
6	PD662
7	PD310, PD663

Parts Supplied:

1. One mounting plate

- 2. One 2" U-bolt kit
- 3. Two ¼ 20 x 1" screws
- 4. Two ¼ 20 hex nuts
- 5. Two #6 32 hex nuts
- 6. Two #6 32 x ³/₄" screws
- 7. Two #6 lockwashers 8. Two ¼" lockwashers
 - 5. TWO 74 TOCKWASh


*Note:

PDA6845 provides two mounting holes for PD687; PDA6545 provides four mounting holes.



MOUNTING KITS FOR PRECISION DIGITAL METERS

PDA6504 PANEL MOUNTING KIT FOR PD650



15.32"(389)

Instructions:

- Drill four holes in panel and make panel cutout as shown. Tolerance for all dimensions is ±0.01 (0.25)
- 2. Secure the two side mounting brackets to the meter base using the supplied hardware.
- 3. Mount this assembly to the rear of the panel using supplied hardware.
- 4. Secure the meter cover to the base.
- 5. Attach decorative bezel to the panel.


Notes:

- 1. Allowable panel thickness: 0.06 0.25 (1.5 6.4). Longer bracket screws may be used for panel thickness up to 0.5 (12.7).
- Mounting space required: 7 x 17.5 x 4 (178 x 445 x 102) (H x W x D). Meter cover extends 0.8 (20) - X from the surface of the panel, where X equals the thickness of the panel.
- This panel mounting kit is not intended to provide waterproof protection to the panel.
- 4. All dimensions are in inches and millimeters (mm).

Parts Supplied:

- 1. Two angle brackets
- 2. One self-adhesive decorative bezel
- 3. Eight #12-24 x ³⁄₄" screws
- 4. Eight #12 lockwashers
- 5. Eight #12-24 hex nuts
- 6. Four #12 flat washers

PDA6554, PDA6604, PDA6624, & PDA6844 PANEL MOUNTING KITS



Instructions:

- 1. Insert the meter through the mounting plate.
- 2. Mount assembly on panel.
- 3. Secure with 4 brackets and 4 screws at corners of the meter. Use washers as needed to allow for panel thickness.

Notes:

- 1. Mounting brackets require 0.8 (20) clearance on either top or side of meter for installation.
- 2. Tolerance for panel cutout dimensions are +0.01/-0.00(+0.3/-0.0).
- 3. Panel mounting kits are not intended to provide waterproof protection to the panel.
- 4. All dimensions are in inches and millimeters (mm).

Parts Supplied:

- 1. One mounting plate (ABS plastic)
- 2. Four self tapping screws
- 3. Four mounting brackets
- 4. Twelve washers

Model **Panel Cutout Required** Mounting Plate Overall Dimensions Allowable Panel Thickness Weight lb (kg) Meter Type 0.060" - 0.25" (1.5 - 6.4) PDA6504 14.30" x 4.97" (363 x 126) 16.28" x 6.98" x 0.25" (414 x 177 x 6) 1.6 (0.7) PD650 PDA6554 6.62" x 5.43" (168 x 138) 7.57" x 6.40" x 0.125" (192 x 163 x 3) PD655 PDA6604 PD660 4.25" x 3.07" (108 x 78) 5.24" x 4.05" x 0.125" (133 x 103 x 3) 0.060" - 0.125" (1.5 - 3.2)0.2 (0.1) PDA6624 PD662 PD675, PD685 PD686, PD697 PDA6844 5.45" x 3.08" (138 x 78) 6.43" x 4.05" x 0.125" (163 x 103 x 3)

LIM6504_G 05/10



ORDERING INFORMATION

PRECISION	DIGITAL	CORPO	RAT	ION
		T 1 (000) 0 10 1001		

89 October Hill Rd • Holliston MA 01746 USA • Tel (800) 343-1001 • Fax (508) 655-8990